



Ebay ID: NationalAssociationofAdoptionCounselorsinc

American Bulldog User Manual Additions

We thank our buyers for their questions which have helped us to augment our User Manual with this document.

1. Installing the Keypad/Dialer Central Unit

Connect your line from your telephone and the line from your telephone company to their respective slots in the Central Unit. Turn the power switch, located in the back of the unit to the "on" position. The POWER light will come on and there will be a beep sound indicating that the unit is functioning properly. You will begin to hear a three beep sound every 30 seconds which is a reminder to set up your phone numbers [program their storage in the unit]. Put your system into an inactive state by entering "1234 Disarm". Program your phone numbers into the Central Unit. To program your phone numbers into the unit you must be in Programming Status. Enter 1234 PRO to enter into Programming Status [the away and home lights will light up]. The three beep sound will stop.

Try to install the Central Unit in a central position in your defensive area and extend the antenna to increase receptive distance. Try installing the Unit away from large metal objects and wireless devices. The alarm system will work even though you may have other wireless devices such as routers in the environment.

2. Installation of Door/Window Sensors

These sensors are used for indicating the status of open and closed windows and doors. Fix the transmitter box and magnetic unit to the door frame and door [window frame and window]. The magnetic unit and the transmitter box should be as close as possible so that they can close the circuit between them. You can screw them into position for an extra strong hold. In order to get the best receiving distance, pull the antenna out and position it. The light on the transmitter box will blink to indicate low battery power. Replace the battery as soon as possible once it starts blinking.

3. Installation of Wireless PIR Motion Sensors

These sensors are used for detecting if someone is moving within a certain space. Fix it on the wall, 6 to 6 1/2 feet high and adjust the position to be facing the defended area. For the pet immune detectors look at the additional instructions that come with them for angling instructions.

4. Installing the Siren

Plug the siren into the siren port of the Central Unit. If you are using the wireless siren then the plug the 'emitter' unit into the siren port of the Central Unit, extend the 'emitter' antenna and face it in the direction of the siren. Only one siren can be used at a time. Sirens do not have to be activated but the length of its sounding time does.

5. Miscellaneous

Zones 01 - 08 are used for motion detectors and other sensors that you want to shut off with the command "Home". The Zones 09 - 32 are always on when your system is activated. One customer wanted a motion detector always on in the garage even when he was home. The solution was to reprogram the motion detector to be in this zone area

Every function that needs programming can only take place when the system is in Programming Status. If the system is in a state of inactivity for 30-40 seconds it will automatically go out of Programming Status. Most complaints that "a function isn't working" occurs because the system wasn't in Programming Status when the function was being programmed.

Command keys need to be pushed firmly and held for one or two seconds to set the system up. Commands such as AWAY, HOME, DISARM, REC are examples.

If the dialer calls out and keeps getting busy signals [when the phone isn't busy] indicates that the phone lines are crossed.

6. This system frees you from professional monitoring services expensive fees and allows you to provide your own monitoring. However, if you want to use a professional monitoring service our system is constructed to work with these professional services. We have found an established professional monitoring service for our customers at very reasonable rates. For additional information contact us at <http://www.americanadoptioncounselors@yahoo.com>